

```

# Конфигурационный файл программы FRN-шлюза (FRNClientConsole)
# Configuration for FRN-gateway (FRNClientConsole)
#
# Revision r6830
# 2021-07-28
#
# http://alterfrn.ucoz.ru

# Основное руководство: http://alterfrn.ucoz.ru/index/freebsd_manual_russian/0-5
# Main manual: http://alterfrn.ucoz.ru/index/manual_russian/0-5

#####
# http://alterfrn.ucoz.ru/index/section_1_auth/0-11
[Auth]
Callsign=XXX01-L
OperatorName=Turku
EMailAddress=xxx01@gmail.com
City=Kaupunki
CityPart=Kaupungin osa tai kylä/pitäjä

# Password
# RU: Пароль, полученный от FRNSysMan по e-почте в процессе регистрации (команда
register),
# или PaSsWoRd, если без регистрации. Пароль не должен быть пустым в любом
случае.
# EN: The password, received from FRNSysMan by e-mail during registration (command
register),
# or PaSsWoRd if no registration. The password can not be empty in any case.
Password=Salasanasi jonka sait rekisteröinin myötä sähköpostisiisi

Country=Finland
Description=ChX/20 / Linux FRN - Gateway AFRN client, r6830
BandChannel=446.06875 FM CTC 131.8
ClientType=GATEWAY

# CharsetName
# RU: Обязательно для UNIX/Linux, необязательно для Windows
# Имя ANSI кодировки FRN это печальное "наследие" оригинального FRN: только
MSWindows, только ANSI.
# Корректной ANSI кодировкой для FRN является текущая ANSI кодировка для вашего
языка на Microsoft Windows.
# Выяснить текущую ANSI кодировку поможет команда "ansi" для консольного
клиента
# Просто запустите на MS Windows команду "C:\FRN\FRNClientConsole.Win32.exe
ansi"
# Для Германии: ISO-8859-1
# Для России: WINDOWS-1251
# EN: Mandatory for UNIX/Linux, optional for Windows
# Name of ANSI charset for FRN is very sad "heritage" of the original FRN: only
MSWindows, only ANSI.
# Correct FRN ANSI charset is default ANSI charset on MS Windows for your
language.
# Command "ansi" for console client will show it for you.
# Just run on command console of your MSWindows with your language: "C:\FRN\
FRNClientConsole.Win32.exe ansi"
# For Germany: ISO-8859-1

```

```
# For Russia: WINDOWS-1251
CharsetName=ISO-8859-1
```

```
#####
```

```
# http://alterfrn.ucoz.ru/index/section_2_audio/0-12
```

```
[Audio]
```

```
#InDevice=ALSA:H3 Audio Codec: CDC PCM Codec-0 (hw:0,0)
```

```
InDevice=ALSA:USB PnP Sound Device: Audio (hw:1,0)
```

```
InSampleRate=48000
```

```
InQuality=H
```

```
InFactor=1
```

```
InPreCapturedTime=
```

```
InAgcEnabled=no
```

```
InAgcLevel=90
```

```
InAgcMaxGain=20
```

```
InHpfEnabled=Yes
```

```
InHpfOrder=5
```

```
InDtmfEnabled=no
```

```
#OutDevice=ALSA:H3 Audio Codec: CDC PCM Codec-0 (hw:0,0)
```

```
OutDevice=ALSA:USB PnP Sound Device: Audio (hw:1,0)
```

```
OutSampleRate=48000
```

```
OutQuality=H
```

```
OutFactor=1
```

```
OutAgcEnabled=no
```

```
OutAgcLevel=90
```

```
OutAgcMaxGain=40
```

```
OutHpfEnabled=Yes
```

```
OutHpfOrder=5
```

```
OutDelayConst=
```

```
#####
```

```
# http://alterfrn.ucoz.ru/index/section_3_radio/0-14
```

```
[Radio]
```

```
PttEnabled=yes
```

```
##### USB-COM for FreeBSD
```

```
#PTT=COM:/dev/cuaU0:RTS:
```

```
#COS=COM:/dev/cuaU0:RS:
```

```
##### RS232 for FreeBSD
```

```
#PTT=COM:/dev/cuau0:RTS:
```

```
#COS=COM:/dev/cuau0:RS:
```

```
##### USB-COM for Linux
```

```
#PTT=COM:/dev/ttyUSB0:RTS:
```

```
#COS=COM:/dev/ttyUSB0:CTS:
```

```
##### RS232 for Linux
```

```
#PTT=COM:/dev/ttyS0:RTS:
```

```
#COS=COM:/dev/ttyS0:CTS:
```

```
##### SYSFS-GPIO for Linux
```

```
PTT=GPIO:9:gpio9:N
```

```
#COS=GPIO:7:gpio7:N - tässä järjestelmässä käytetään GPIO - pinnien kautta..
```

```
##### CM108-GPIO for FreeBSD/Linux
#PTT=CM108:/dev/hidraw0:GPIO3:N
#COS=CM108:/dev/hidraw0:VOLDN:I
```

```
#### VOX
COS=VOX:100
```

```
LIGHT=
STATIC=
CTCSSWakeTime=0
CarrierCatchTime=150
CarrierLostTime=600
SquelchSettlingTime=
DtmfTimeout=15
DtmfCommands=
IdNoSoundListFileName=
```

```
#####
# http://alterfrn.ucoz.ru/index/section_4_manager/0-15
[Manager]
ManagerAddress=sysman.freeradionetwork.de
ManagerPort=10025
DynamicPasswordMode=YES
```

```
#####
# http://alterfrn.ucoz.ru/index/section_5_server/0-16
```

```
[Server]
ServerReconnectCount=6
ServerReconnectInterval=6000
```

```
# Адрес FRN-сервера, к которому есть желание подключиться
# FRN-server address you wish connect to
ServerAddress=fin.frn.fi
```

```
ServerPort=10024
VisibleStatus=AV
Network=Varsinais-Suomi
BackupServerMode=YES
ForcedBackupServerAddress=fin2.frn.fi
ForcedBackupServerPort=10024
ForcedBackupServerNetwork=Varsinais-Suomi
```

```
RxTxHookScript=
InvalidStaticPasswordScript=
```

```
ProtoListFormat=DIFF
ProtoSpeakerInfo=yes
ProtoShortFrames=yes
```

```
#####
# http://alterfrn.ucoz.ru/index/serction_6_internet/0-17
[Internet]
ProxyType=NONE
ProxyAddress=192.168.1.1
ProxyPort=3128
```

CharsetName=UTF-8  
PreferIPv4=yes

```
#####  
# http://alterfrn.ucoz.ru/index/section_7_message/0-18  
[Message]  
PrivateAutoResponse=<a href="https://frn.fi"> Katso lisää.</a>  
MessageHookScript=
```

```
#####  
# http://alterfrn.ucoz.ru/index/section_8_system/0-19  
[System]  
WriteDir=.
```

```
# CharsetName  
# Ru: Имя системной кодировки символов для консольного вывода,  
#     если эта кодировка не была корректно определена из  
#     системных настроек операционной системы, например,  
#     из переменных LANG и/или другим способом.  
# En: The name of the system charset encoding for console output,  
#     if the encoding was detected incorrectly from  
#     LANG variable or/and any other ways.  
CharsetName=
```

```
PidFile=/run/frnclient.pid  
LogFile=/opt/FRNClient/frnclient.log  
LogControlSound=Yes  
LogExternalSound=Yes  
LogClientList=Yes  
LogCarrier=Yes  
LogTiming=Yes  
LogBackupServerMode=Yes  
LogCheckServer=Yes  
LogDtmfTones=Yes  
LogDtmfCommands=Yes  
LogClientListDelimiter=;  
LogCache=no  
LogPTT=no
```

```
#####  
# http://alterfrn.ucoz.ru/index/section_9_sounds/0-21  
[Sounds]  
SoundsDir=sounds  
SoundCourtesy=Nextel.wav  
EnableCourtesy=Yes  
SoundCourtesyEmptyNet=  
EnableCourtesyEmptyNet=  
SoundRoger=  
EnableRoger=No  
SoundNoConnection=3down.wav  
EnableNoConnection=Yes  
SoundReject=4down.wav  
EnableReject=Yes  
SoundError=  
EnableError=  
SoundRadioBOT=  
EnableRadioBOT=  
EnableConnect=no
```

SoundConnect=  
ConnectSoundCfgEnabled=no  
ConnectSoundCfgFileName=  
ConnectSoundExtEnabled=no  
ConnectSoundExtScript=  
ConnectSoundExtDir=  
EnableServerBOT=no  
SoundServerBOT=  
EnableServerEOT=no  
SoundServerEOT=  
EnableDisconnect=no  
SoundDisconnect=

```
#####  
# http://alterfrn.ucoz.ru/index/section_10_hours/0-22  
[Hours]  
Enabled=Yes  
Dir=hours/fi  
Interval=60  
Correction=0  
Debug=no  
ExtEnabled=No  
ExtScript=  
ExtDir=  
ExtTempDir=
```

```
#####  
# http://alterfrn.ucoz.ru/index/section_11_informer/0-23  
[Informer]  
Enabled=No  
Dir=  
Interval=900  
Mode=SEQ  
SilenceEnabled=No  
SilenceInterval=300  
SilenceTime=2000  
ExtEnabled=No  
ExtScript=  
ExtDir=  
ExtTempDir=
```

```
#####  
# http://alterfrn.ucoz.ru/index/section_12_recorder/0-25  
[Recorder]  
Enabled=No  
Dir=./recorder  
Direction=both  
FileNameFormat=long  
SubdirMode=y-m-d  
Script=
```

```
#####  
# http://alterfrn.ucoz.ru/index/section_13_command/0-30  
[Command]  
CommandEnabled=yes
```

CommandPort=10027  
CommandIPVersion=46  
CommandPreferIPv4=yes  
AmplitudeEnabled=No  
AmplitudePort=10028